


5 Exploded View and Parts List

- You can search for updated part codes through ITSELF web site.

URL : <http://itself.sec.samsung.co.kr/>


5-1 LE26S81BH Exploded View



5-2 LE26S81BH Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04750F	ASSY COVER P-FRONT;26S81,EO(HOTEL),,ABS+	1	S.A	
T0175	BN96-04769A	ASSY SPEAKER P;16ohm,4pin,5W,Jasmine 23"	1	S.A	
M0215	BN07-00364A	LCD-PANEL;V260B1-L04,6bit+FRC,26inch,16.	1	S.A	
T0447	BN96-04682F	ASSY BRACKET P-PANEL;26S81,AUO,SEH	1	S.N.A	
M0146	BN61-02205B	BRACKET-PANEL TOP;Bordeaux 26,SECC,T1.2	1	S.N.A	
M0115	BN61-02931A	BRACKET-STAND LINK;JASMINE 26,SECC,T1.6	1	S.A	
M0014	BN94-01580B	ASSY PCB MAIN;Jasmine 26"	1	S.N.A	
M0027	BN96-04745A	ASSY STAND P-BASE;-;22,23,26S81,-,ABS+PM	1	S.A	
M0013	BN96-04820C	ASSY COVER P-REAR;26S81,EO(HOTEL),,HIPS,	1	S.A	

5-3 LE32S81BH Exploded View




5 Exploded View & Parts List

5-4 LE32S81BH Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04694N	ASSY COVER P-FRONT;32S81,EQ(HOTEL),ABS+P	1	S.N.A	
T0175	BN96-04770A	ASSY SPEAKER P;8ohm,4pin,10W,Jasmine 32"	1	S.A	
M0215	BN07-00348A	LCD-PANEL;V315B1-L01,8bit,31.5inch,16.7M	1	S.A	
AUO V9	BN07-00421A	T315XW02(V9),8bit,760.0*450.0*47.25,16.7M,16:9,0.51*0.51,0 to +50.5V, AMVA 72%,AMVA 72%			
AMLCD VE	BN07-00453A	LTA320WT-L06,8bit,32inch,16.7M,16:9,0.51075(H)*0.51075(W,0 to +50.5V,SMVA 72%,32 inch			
CPT-EMVA	BN07-00460A	CLAA320WF01SC,8bit,32inch,16.7M,16:9,0.51075(H) i 0.51075,0 to +50, 12V,EMVA 75% ZBD,32 inch HD			
T0447	BN96-04681A	ASSY BRACKET P-PANEL;- ,32R81,-,-,-,-,AM,	1	S.N.A	
M0146	BN61-02207A	BRACKET-PANEL SIDE;Bordeaux 26,SECC,T1.2	4	S.N.A	
T0764	BN44-00156A	SMPS-LCDTV;MK32P,SEM,AC/DC,180W,AC100 ~	1	S.A	
T0531	BN63-03093B	COVER-BOTTOM;32S81,HIPS,-,-,-,-,HB,-,BK500	1	S.A	
M0115	BN61-02947A	BRACKET-STAND LINK;JASMINE 32",SECC,T1.6	1	S.N.A	
M0014	BN94-01429L	ASSY PCB MAIN;BN94-01429D,839E	1	S.A	
M0027	BN96-04697B	ASSY STAND P-BASE;- ,32S8,-,ABS+PMMA,BK23	1	S.A	
M0013	BN96-04698D	ASSY COVER P-REAR;32S81,EQ(HOTEL),,HIPS,	1	S.A	

5-5 LE37S81BH Exploded View




5 Exploded View & Parts List

5-6 LE37S81BH Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04752H	ASSY COVER P-FRONT;37S81,EO(HOTEL),ABS+P	1	S.A	
T0175	BN96-04770B	ASSY SPEAKER P;8ohm,4pin,10W,600/1250mm,	1	S.A	
M0215	BN07-00366A	LCD-PANEL;CLAA370WA03,8bit,37inch,16.7M,	1	S.A	
AUO	BN07-00393A	T370XW02,8bit,37inch,16.7M,16:9,0.6(H)*0.6(W),0 to +50,12V,AMVA 72%,37inch			
T0447	BN96-04680E	ASSY BRACKET P-PANEL;37S86,EO	1	S.N.A	
M0146	BN61-02241A	BRACKET-PANEL SIDE;Bordeaux 37,SECC,T1.2	1	S.N.A	
M0146	BN61-02242A	BRACKET-PANEL SIDE;Bordeaux 37,SECC,T1.2	1	S.N.A	
T0764	BN44-00157A	SMPS-LCDTV;MK37,SEM,AC/DC,280W,AC100 ~ 2	1	S.A	
T0531	BN63-03127B	COVER-BOTTOM;37,40S81,HIPS,-,-,HB,-,BK	1	S.A	
M0107	BN63-03039A	SHIELD-COVER;MURANO40,PCM,T0.5,IDTV	1	S.N.A	
M0115	BN61-02882A	BRACKET-STAND LINK;TULIP,40,SECC,T1.6,-,	1	S.N.A	
M0014	BN94-01593A	ASSY PCB MAIN;37 INCH,JASMINE	1	S.A	
M0027	BN96-04754A	ASSY STAND P-BASE;-,-,37,40S81,-,ABS+PMMA,	1	S.A	
M0013	BN96-04826D	ASSY COVER P-REAR;37S81,EO(HOTEL),,HIPS,	1	S.A	

5-7 LE40S81BH Exploded View




5 Exploded View & Parts List

5-8 LE40S81BH Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04753C	ASSY COVER P-FRONT;40S86,EO,ABS+PMMA,HB,	1	S.A	
T0175	BN96-04770B	ASSY SPEAKER P;8ohm,4pin,10W,600/1250mm,	1	S.A	
M0215	BN07-00370A	LCD-PANEL;T400XW02,8bit,40inch,16.7M,16:	1	S.A	
AMLCD	BN07-00387A	LTA400WT-L06,8bit,40inch,16.7M,16:9,0.648(H)*0.216(W)*3,0 to +50, 12V,SPVA 72% ZBD,40 inch HD			
AUO VE	BN07-00448A	T400XW01 V1,8bit,40inch,16.7M,16:9,0.648(H)*0.648(W),0 to +50,5V,AMVA,72%,40 inch, AMVA			
AMLCD VE	BN07-00451A	LTA400WT-L07,8bit,40inch,16.7M,16:9,0.648(H)*0.648(W),0 to +50,12V,SMVA 72%,40 inch			
T0447	BN96-04679A	ASSY BRACKET P-PANEL;BORDEAUX PLUS40	1	S.N.A	
M0146	BN61-02256B	BRACKET-PANEL SIDE;Bordeaux 40,SECC,T1.2	1	S.N.A	
M0146	BN61-02257B	BRACKET-PANEL SIDE;Bordeaux 40,SECC,T1.2	1	S.N.A	
T0531	BN63-03127B	COVER-BOTTOM;37,40S81,HIPS,-,-,HB,-,BK	1	S.A	
M0115	BN61-02882A	BRACKET-STAND LINK;TULIP,40,SECC,T1.6,-,	1	S.N.A	
M0014	BN94-01193D	ASSY PCB MAIN;LE40S86BDX/*	1	S.A	
M0027	BN96-04754A	ASSY STAND P-BASE;37,40S81,ABS+PMMA,HB,B	1	S.A	
M0013	BN96-04822B	ASSY COVER P-REAR;40S86,EO,HIPS,HB,BK500	1	S.A	

5-9 LE46S81BH Exploded View



5 Exploded View & Parts List

5-10 LE46S81BH Parts list

Location	Code.No	Item & Specification	Q'ty	SA/SNA	Remark
T0003	BN96-04738B	ASSY COVER P-FRONT;46S81,EO,ABS+PMMA,HB,	1	S.A	
T0175	BN96-04770C	ASSY SPEAKER P;8ohm,4pin,10W,750/1250mm,	1	S.A	
M0215	BN07-00389A	LCD-PANEL; LTA460WT-L11,8bit,46inch,16.7	1	S.A	
AMLCD VE	BN07-00452A	LTA460WT-L12,8bit,46inch,16.7M,16:9,0.7455(H)*0.7455(W),0 to +50, 12V,SMVA 72%,46 inch			
T0447	BN96-05214D	ASSY BRACKET P-PANEL;46S81,KO	1	S.N.A	
T0531	BN63-03185B	COVER-BOTTOM;46S81,HIPS,-,-,-,HB,-,BK500	1	S.A	
M0014	BN94-01194R	ASSY PCB MAIN-AMLCD;LE46S81BX/*	1	S.A	
M0027	BN96-04743A	ASSY STAND P-BASE;46S81,ABS+PMMA,HB,BK23	1	S.A	
M0013	BN96-04825A	ASSY COVER P-REAR;46S81,EO,HIPS,HB,BK500	1	S.A	