

CAUTION
HIGH VOLTAGE
HR®
AYUDA AL SERVICIO
INVERTER CATALOG
2008

If you need more information on Computer and Electronic Repair, please visit these websites to improve yourself.

http://www.fastrepairguide.com
http://www.protech2u.com
http://www.plasma-television-repair.com
http://www.lcd-television-repair.com

Happy Repairing!!


Highly Recommended Repair Ebook:



If you're a LCD Monitor repairer, then this is the best guide for you. Why? Because, the author revealed all his LCD Monitor Repairing secrets for you. I think, with just few Repair tips you learned from this guide you will get back your investment!
Click Here to read more.



This eBook will show you how to test the electronic component correctly and accurately. Some of you may say that I don't need this eBook because it is too simple! Do you know that, in fact there is lots of testing electronic components secrets I have learned from this guide? Do you know how to test a'TRIAC' correctly and accurately? If you answer no then I guess you have to get this EBook. Click Here to read more.



Are you tired of searching the service manuals to look for the value of a burnt resistor? If the answer is YES, then this eBook is a 'must have' guide for you. You can save a lot of time and be able to repair customer's Electronic equipment with burnt resistors in it.
Click here to read more.

Ref. orig.	HR	Panel LCD	Marca/Brand	Model.
INVERTERS 4 LAMPARAS				
FIF1742-57A GH116A 19-4003C	**I04L10002**	SAMSUNG LTM190E1-L01/02/03 LTM19E4-L01/02 SHARP LQ150XLGB1/LW71		
FIF1742-57B 1942-32D	**I04L10003**	SAMSUNG LTM190EX-L01/05/21 LTM550V1 AUOPTRONICS M170EG01/EN07 M190EG01/02 M190EN02/03/04 T150XG01		
GH053A(A2) GH027A GH027A(A3) FIF1742-31C FIF1742-34B	**I04L10004**	SAMSUNG LTM170EU-L01/11/21 LTM170EX-L01 / LTM170E4/E5/E6/E8 LG-PHILIPS LC130V01-A2 / LM190E3 LC150X01-C3/X02-A4 LM170E01-A4/TLA1 / LM171W01 SHARP LQ150X1LGB1 / LQ150X1LW71	PHILIPS	CH. LC4.1E AB
GH027I FIF1542-31B 30018343 30041724	**I04L10005**	SAMSUNG LTM150XH-L01/L06 LTM170XH-L01/06/T01 LG-PHILIPS LC130V01-A2 LC150X01-C3/X02-A4 CHIMEI M150X3-L04/06 - V150X1L06 /X2T06 LQ150X1LGB1 / LQ150X1LW71 SHARP LQ150X1LW71/N HYDIS HT15X13-100	PHILIPS	13PF7835
GH140A(A1) GH017 GH017A3 3373400 PLCD2615412	**I04L10007**	SAMSUNG LTM150XH-L01/06A LTM170EH-L05 LG-PHILIPS LC130V01-A2 LC150X01-C3/X02-A4 CHIMEI M150X3-L04/06 - V150X1L06 /X2T06 LQ150X1LGB1 / LQ150X1LW71 SHARP LQ150X1LW71/N HYDIS HT15X13-100	PHILIPS	13PF7835

GH053A(A6) FIF1542-02 9965 000 17796	**I04L10010**	SAMSUNG LTM170EX-L21 / LTM190EX-L21/31 LTM170W1 / LTM550V1 LG-PHILIPS LM190E05-SL01/03 QD14VL03-01 AUOPTRONICS M170EN01/02/03/04 - M170EG01/02/04 M190EG01/02/04 NEC 170SX01TB HANNSTAR HSD190ME12/13	PHILIPS	15FT9955
FIF1942-67A	**I04L10014**	SAMSUNG LTM170EX-L01 - LTM170EU-L01/11/21/25 LTM170E06-L02/04 - LTM190EXL01/05/21 LG-PHILIPS LM170E01/02 - LM171W01 LM190E03/04/05 - LM190WX1-TLA1 CHIMEI M170EG01-V0 M190EN02/03/04 HYDIS HT17E11-200/300 - HT17E12/13		

INVERTERS 6 LAMPARAS

FIF1766-31A GH103A 30041927 30029602	**I06L10001**	LG-PHILIPS LC171W03-A4/B3 LM171W03-A04 LC150X01-SL01/A3	JVC JVC JVC JVC	LT17B60 LT17C50 LT17D50 LT17E31
FIF1766-36A DA3602-01	**I06L10004**	LG-PHILIPS LC150X01-A3		
GH096A DA2605-01	**I06L10006**	FUJITSU FLC48SXC8V-05 FLC48SXC8V-12 / F SHARP LQ190E1LW41		
FIF2066-50A	**I06L20001**	AUOPTRONICS A201SN02		
GH164A DA2604-02	**I06L20002**	SAMSUNG V201V1-T01 NEC NL128102BC28/29 - NL16010BC27-02/03 CHUNGHWA CLAA201VA07 SHARP LQ181E1LW31 LQ210U1LW11	PHILIPS GRUNDIG GRUNDIG JVC	20PF4121 LCD51-4505 LCD51-6605 LT20E50

		AUOPTRONICS A201SN01-V5 / A201SN02-V4 T200XW02-V0	
FIF2064-31B	**I06L20003**	SAMSUNG LTM201U1-L01 LTM201M1-L01 LG-PHILIPS LM190E01-A4/SL01 - LM190E02-B4 LM190E05-SL02 - LM201W01-A5/B5 LC201V2-A3/SD02	
GH089A DA6303-01 FIF2066-31A	**I06L20004**	SAMSUNG LTM210M2-L01 LTM213U6-L01 LG-PHILIPS LC201U02 - LC201V01/02 LM190E01/E05 LM201U03/04 - LM201V02-A3 AUOPTRONICS M201EW01 M201UN02 NEC 201VBTB	
GH158A FIF2066-01A	**I06L20007**	SAMSUNG LTM201U1-L01 LTM213U6-L01	
FIF2066-51C FIF2066-51D	**I06L20009**	SAMSUNG LTM213U3 / U4 / U5	SAMSUNG
QF131V1.00	**I06L20012**	AUOPTRONICS A201SN01-V5 / A201SN02-V4 CHIMEI V201V1-T01	SANYO CE 20 L01 WELTSTAR 20 LF1T VESTEL CH.17SC.07-2
LIVP6009 30045614 PLCD0318604 LVE0321	**I06L20014**		JVC LT20E50 LT20A5S VESTEL
LIVP6010 30045615	**I06L20015**		VESTEL
BI2036C	**I06L20019**	AUOPTRONICS CHIMEI	SOGO SS2002

INVERTERS 10 LAMPARAS

VIT70008.50 27-D000466	**I10L20001**		

INVERTERS 12 LAMPARAS

GH151A GH214A BN44-00136A	**I12L20002**	SAMSUNG LTA240M1-L02 LTM240M1-L01/02 LTM240M2-L01/02	SAMSUNG
GH194A LJ97-00863A	**I12L20003**	SAMSUNG LTA230W-L02 LTA230W1-L02 /04 /07	SAMSUNG LA23R51B LE23R41B LE23R51B CH.RE23
GH199A LJ97-00942A	**I12L20004**	SAMSUNG LTA260W3-L03 LTM260W3-L03	SAMSUNG LA23R51B LE23R41B LE23R51B CH.RE23
GH212A LJ97-01069A	**I12L20005**	SAMSUNG LTA230W2-L01 LTA230W2-L0100R7	SAMSUNG
FIF2412-32A	**I12L20006**	SAMSUNG LTM240CT01 LTM240M1-L01/02 LTM240M2-L02 AUOPTRONICS LTM240M1-L01/02 LTM240M2-L01/02	SAMSUNG
VIT71007.50 19.26006.063	**I12L20007**		

INVERTERS 14 LAMPARAS

VIT79005.81 19.26006.288	**I14L20001**	QDI V26D3	
VIT79002.52 19.26006.286	**I14L30001**	QDI V32C5 V32C1-CD	
VIT79002.62 19.26006.137	**I14L30002**	QDI V32C5 V32C1-CD	

INVERTERS 16 LAMPARAS

GH178A LJ97-00732C	**I16L20001**	SAMSUNG LTM270M1-L01	SAMSUNG
VIT71008.90 19.26006.111	**I16L20002**	AUOPTRONICS T260XW02	
VIT71008.91 19.26006.167	**I16L20003**		
VIT71008.92 19.26006.187	**I16L20004**		

GH169A GH169C LJ97-01265A	**I16L30001**	SAMSUNG LTM300M1-P01	SAMSUNG
VIT79001.52 19.26006.301	**I16L30004**	QDI V32C1 V32D2	
VIT68001.80 4H.V1448.451/C1	**I16L30005**	CHUNGHWA CLAA320WF01T CLAA320WB02S	SAMSUNG LE32S62B
VIT68004.70 4H.V1838.491/B1	**I16L30006**	CHUNGHWA CLAA370WF01 CLAA370WA03S	SAMSUNG LE37S62B

INVERTERS 18 LAMPARAS

VIT79006.60 19.26006.294	**I18L30001**	AUOPTRONICS V37A1	

INVERTERS 20 LAMPARAS

VIT71010.53 19.26006.146	**I20L30001**	AUOPTRONICS T370XW01	
VIT70006.60 27-D005816	**I20L30002**	CHIMEI V370H1-24A	
VIT70006.80 27-D015041	**I20L30003**	CHIMEI V370H1-L0A	
VIT70023.50/51 27-D005861	**I20L40001**	CHIMEI V420H1-L24	
VIT70023.60/61 27-D013345	**I20L40002**	CHIMEI V420H1-20C	
VIT70023.70/71 27-D010636	**I20L40003**	CHIMEI V420H1-20A	

POWER INVERTER 2 LAMPARAS

AI0021A 3138 188 79062	**IP2L10001**	LG-PHILIPS	PHILIPS
AI0067A 3138 198 74361	**IP2L10002**	LG-PHILIPS	PHILIPS
AIP0097A 3138 198 76371	**IP2L10003**	LG-PHILIPS	PHILIPS

POWER INVERTER 4 LAMPARAS

AIP0093 3138 198 75863	**IP4L10001**	LG-PHILIPS	PHILIPS
AIP0095 FE572A306A0001	**IP4L10002**	LG-PHILIPS	LG
AI0031F	**IP4L10006**	LG-PHILIPS	LG

FE5319C249G0885			VESTEL
AIP0105N FE6427A324N0406	**IP4L10007**	LG-PHILIPS	LG VESTEL

POWER INVERTER 6 LAMPARAS

AIV0001A FE7025O280K1075	**IP6L20001**	LG-PHILIPS	PHILIPS
AIVP0010 FE5N03C319A	**IP6L20002**	LG-PHILIPS	LG
AIVP0026 / C 30051308 30057403	**IP6L20003**	LG-PHILIPS SAMSUNG	SANYO CE20LD51C VESTEL CH.17MB24-3
AIV0006C FE6406A280G0179	**IP6L20004**	LG-PHILIPS	LG
AIV0009A FE7026N280Q0161	**IP6L20005**	LG-PHILIPS	PHILIPS
AIVP0032A E7ND0326364020033	**IP6L20006**	LG-PHILIPS	VESTEL
AIP0110A FE7425A325A0070	**IP6L20009**	LG-PHILIPS	LG

POWER INVERTER 16 LAMPARAS

AIVP0035A 30053669	**IP16L30001**	AUOPTRONICS CHUNGHWA	VESTEL

INVERTER ORIGINAL REFER. EQUIVAL.
FIF1742-57A
GH116A
FIF1942-32C



Dimensiones / size : 160mm x 26mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Bri.	GND

LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM190E1-L01/02/03 LTM190E4-L01/02 LTM170EU-L01 / LTM170EX-L01
SHARP	LQ150X1LGB1/LW71
CHIMEI	M170E06-L02 / M190E02-L01

Marca / Brand	Model

Observaciones / Remarks

HR I04L10003

INVERTER ORIGINAL REFER. EQUIVAL.
FIF1742-57B
FIF1942-32D



Dimensiones / size : 160mm x 26mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Bri.	GND

LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM190EX-L01/05/21 LTM550V1
LG-PHILIPS	LM190E01-A4 / C4
AUOPTRONICS	M190EG01/EN07 - M190EN02/03/04 M170EG01/EN07 - T150XG01

Marca / Brand	Model

Observaciones / Remarks

HR I04L10004

INVERTER ORIGINAL REFER. EQUIVAL.
GH053A(A2) - GH027A FIF1742-31C FIF1742-34C



Dimensiones / size : 160mm x 26mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Bri.	GND

LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM170EU-L01/11/21 LTM170E4-E5/E6/E8 - LTM170EX-L01
SHARP	LQ150X1LGB1 - LW71
LG-PHILIPS	LM170E01-A4 / TLA1 - LM171W01 LM190E3 - LC150X01-C3 / X02-A4
CHIMEI	M170E05-L01/04/05/08 -M190A01/E05
AUOPTRONICS	M170XW01-M190EG / EN02

Marca / Brand	Model
PHILIPS	CHASIS LC4.1E AB

Observaciones / Remarks

HR I04L10005

INVERTER ORIGINAL REFER. EQUIVAL.
GH027I
FIF1542-31B
30018343



Dimensiones / size : 160mm x 26mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Bri.	GND

LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM170EU-L01/11/21-LTA150XH-L01 LTM170E4-E5/E6/E8 - LTM170EX-L01
LG-PHILIPS	LC130V01-A2
CHIMEI	M150X3-L04/06 V150X1-L06 / V150X2-T06
SHARP	LQ150X1LW71N
HYDIS	HT15X13-100 / 200

Marca / Brand	Model
PHILIPS	13PF7835

Observaciones / Remarks

HR I04L10007

INVERTER ORIGINAL REFER. EQUIVAL.
GH140A(A1) GH017 3373400



Dimensiones / size : 158mm x 39mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Bri.	GND

LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM150XH-L01/06A LTM170EU-L01/11/21/25 LTM170XH-L01/06/T01 LTM190M2-L01
CHIMEI	M190E05-L0A/0E
LG-PHILIPS	LM190E05-SL01/03 QD14VL03-01
SHARP	LQ150X1LGB1 - LQ150X1LW71

Marca / Brand	Model
PHILIPS	14PF6826
BEKO	NR17 CD LE3

Observaciones / Remarks
Para GH017 requiere fijacion mediante cinta adhesiva
For use in replacement of GH017 adhesive tape must be used.

HR I04L10010

INVERTER ORIGINAL REFER. EQUIVAL.
GH053A(A6) FIF1542-02A FIF1742-07B



Dimensiones / size : 160mm x 26mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Bri.	GND


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM170EX-L21 - LTM170W1 LTM190EX-L21 / L31 - LTM550V1
LG-PHILIPS	LM190E05-SL01 / 03 - QD14VL03-01 LC151X01-03
AUOPTRONICS	M170EN01/02/03/04-M170EG01/02/04 M190EG01 / 02 / 04 - T150XG01
NEC	170SX01TB
HANNSTAR	HSD190ME12 /13

Marca / Brand	Model
PHILIPS	15FT9955 CHASIS LC 03 E

Observaciones / Remarks

HR I04L10014

INVERTER ORIGINAL REFER. EQUIVAL.
FIF1942-67A



Dimensiones / size : 180mm x 45mm

Conector control / Control connector							
8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	GND	on-off	Br.

LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM170EU-L01/11/21/25 LTM170EX-L01 - LTM170E06-L02/04 LTM190EX-L01/05/21/31
HYDIS	HT17E11 / E12 / E13
LG-PHILIPS	LM170E01 / 02 - LM171W01 LM190E03 / 04 / 05 - LC150X02 LM190WX1-TLA1
CHIMEI	M170EG01-V01 M190EN02/03/04 - M190PW01-V0

Marca / Brand	Model

Observaciones / Remarks

HR I06L10001

INVERTER ORIGINAL REFER. EQUIVAL.
FIF1766-31A GH103A V30029602



Dimensiones / size : 160mm x 55mm

Conector Control / Control Connector											
1	2	3	4	5	6	7	8	9	10	11	12
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Br.	GND

LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	LC171W03-A4 / B3 LM171W03-A04 LC150X01-SL01 / A3


Marca / Brand	Model
JVC	LT17B60 LT17C50 LT17D50 LT17E31

Observaciones / Remarks
Para GH103A deben eliminarse las tres ultimas conexiones (13-14-15) del conector de control.

For use in replacement for GH103A, the last connections (13-14-15) of control cable must be eliminated.

HR I06L10004

INVERTER ORIGINAL REFER. EQUIVAL.
FIF1766-36A DA3602-01



Dimensiones / size : 192mm x 50mm

Conector Control / Control Connector											
1	2	3	4	5	6	7	8	9	10	11	12
12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Br.	GND


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	LC150X01- A3 LC150X01- S01

Marca / Brand	Model

Observaciones / Remarks

HR I06L10006

INVERTER ORIGINAL REFER. EQUIVAL.
GH096A DA2605-01



Dimensiones / size : 188mm x 70mm

Conector Control / Control Connector														
15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Br.	GND


LCD panel manuf.	LCD Panel cod.
SHARP	LQ190E1LW41
FUJITSU	FLC48SXC8V-05 FLC48SXC8V-12 / F

Marca / Brand	Model
SHARP	

Observaciones / Remarks

HR I06L20001

INVERTER ORIGINAL REFER. EQUIVAL.
FIF2066-50A



Dimensiones / size : 188mm x 60mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	GND	GND	GND	GND	GND	on-off	GND	Br.	GND


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	A201SN02

Marca / Brand	Model

Observaciones / Remarks

HR I06L20002

INVERTER ORIGINAL REFER. EQUIVAL.
GH164A DA2604-02



Dimensiones / size : 160mm x 55mm

Conector Control / Control Connector							
1	2	3	4	5	6	7	8
12V	12V	12V	GND	GND	GND	Br.	on-off


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	A201SN01-V5 - AS201SN02-V4 T200XW02-V0
LG-PHILIPS	LM190E05-SL01 / 03 - QD14VL03-01
CHIMEI	M201V1-T01 - V201V1-T01
NEC	NL128102BC28/29 - NL16010BC27-02
SAMSUNG	V201V1-T01
CHUNGHWA	CLAA201VA07

Marca / Brand	Model
PHILIPS	20PF4121
GRUNDIG	LCD51-4505 LCD51-6605
JVC	LT20E50

Observaciones / Remarks

HR I06L20003

INVERTER ORIGINAL REFER. EQUIVAL.
FIF2064-31B



Dimensiones / size : 188mm x 50mm

Conector Control / Control Connector									
1	2	3	4	5	6	7	8	9	10
Br.	N.C.	GND	GND	on-off	12V	GND	GND	12V	12V


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM201U1-L01 / LTM201M1-L01 LTM170E4-E5/E6/E8 - LTM170EX-L01
LG-PHILIPS	LM190E01-A4/SL01 LM190E02-B4 - LM190E05-SL02 LM201W01-A5/B5 LC201V2-A3 / SD02

Marca / Brand	Model

Observaciones / Remarks

HR I06L20004

INVERTER ORIGINAL REFER. EQUIVAL.
GH089A
DA6303-01
FIF2066-31A



Dimensiones / size : 188mm x 70mm

Conector Control / Control Connector														
15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
12V	12V	12V	12V	12V	12V	GND	GND	N.C.	GND	GND	on-off	GND	Br.	GND


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	LC201U02 - LC201V01 / 02 LM201U03/U04 - LM201V02-A3 LM190E01/E05
AUOPTRONICS	M201EW01 - M201UN02
NEC	201VBTB
SAMSUNG	LTM210M2-L01

Marca / Brand	Model
PHILIPS	20PF4121
GRUNDIG	LCD51-4505 LCD51-6605
JVC	LT20E50

Observaciones / Remarks

HR I06L20007

INVERTER ORIGINAL REFER. EQUIVAL.
GH158A FIF2066-01A



Dimensiones / size : 170mm x 62mm

Conector Control / Control Connector														
15	14	13	12	11	10	9	8	7	6	5	4	3	2	1
15V	15V	15V	15V	15V	15V	GND	GND	N.C.	GND	GND	on-off	GND	Br.	GND


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM201U1-L01

Marca / Brand	Model

Observaciones / Remarks

HR I06L20009

INVERTER ORIGINAL REFER. EQUIVAL.
FIF2066-51C FIF2066-51D



Dimensiones / size : 188mm x 60mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
15V	15V	15V	GND	GND	GND	GND	GND	on-off	GND	Br.	GND


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM213U3 LTM213U4 / U5

Marca / Brand	Model

Observaciones / Remarks

HR I06L20012

INVERTER ORIGINAL REFER. EQUIVAL.
QF131V1.00 30022526 3108743



Dimensiones / size : 160mm x 55mm

Conector Control / Control Connector							
1	2	3	4	5	6	7	8
12V	12V	12V	GND	GND	GND	Br.	on-off


LCD panel manuf.	LCD Panel cod.
SAMSUNG	V201V1-T01
AUOPTRONICS	A201SN01 / 02
CHIMEI	V201V1-T01

Marca / Brand	Model
SANYO	CE 20 L01
WELTSTAR	W 20 TFT 20 LF 1T CH.17SC 07-2

Observaciones / Remarks
Se adjuntan instrucciones para colocacion del inverter.
Instructions to place the inverter are attached in the box.

HR I06L20014

INVERTER ORIGINAL REFER. EQUIVAL.
LIVP6009 - 30045614
LVE0321 - 30031727
PLCD0318604



Dimensiones / size : 180mm x 55mm

Conector Control / Control Connector							
1	2	3	4	5	6	7	8
12V	12V	12V	GND	GND	GND	Br.	on-off


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	A201SN01-V5

Marca / Brand	Model
JVC	LT20E50 LT20A5S
VESTEL	

Observaciones / Remarks

HR I06L20015

INVERTER ORIGINAL REFER. EQUIVAL.
LIVP6010 - 30045615



Dimensiones / size : 180mm x 55mm

Conector Control / Control Connector							
1	2	3	4	5	6	7	8
12V	12V	12V	GND	GND	GND	Br.	on-off


LCD panel manuf.	LCD Panel cod.

Marca / Brand	Model
VESTEL	

Observaciones / Remarks

HR I06L20019

INVERTER ORIGINAL REFER. EQUIVAL.
BI2036C



Dimensiones / size : 188mm x 60mm

Conector Control / Control Connector											
12	11	10	9	8	7	6	5	4	3	2	1
15V	15V	15V	GND	GND	GND	GND	GND	on-off	GND	Br.	GND

LCD panel manuf.	LCD Panel cod.
SAMSUNG	V201V1-T01
AUOPTRONICS	A201SN01 / 02
CHIMEI	V201V1-T01


Marca / Brand	Model
SOGO	SS 2002

Observaciones / Remarks
Se adjuntan instrucciones para adaptar conexión cable control inverter original.

Instructions to adapt control cable connection of original inverter included in the box.

HR I10L20001

INVERTER ORIGINAL REFER. EQUIVAL.
VIT70008.50
27-D000466
I201B1-24-V02-L1H1



Dimensiones / size : 200mm x 100mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	N.C.	Pwm	on-off


LCD panel manuf.	LCD Panel cod.
CHIMEI	V201B1-V02-L1H1

Marca / Brand	Model

Observaciones / Remarks

HR I12L20002

INVERTER ORIGINAL REFER. EQUIVAL.
GH151A GH214A BN44-00136A



Dimensiones / size : 272mm x 95mm

Conector Control / Control Connector													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.A	Pwm


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTA240M1-L02 LTM240M1-L01/02 LM240M2-L01/02

Marca / Brand	Model
SAMSUNG	

Observaciones / Remarks

HR I12L20003

INVERTER ORIGINAL REFER. EQUIVAL.
GH194A LJ97-00863A



Dimensiones / size : 272mm x 95mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	P.det.	on-off	Br.A	Pwm

CN8			
1	2	3	4
GND	on-off	Br.A	Pwm


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTA230W-L02 LTA230W1-L02/04/07

Marca / Brand	Model
SAMSUNG	LA23R51B LE23R41B LE23R51B CH. RE23

Observaciones / Remarks

HR I12L20004

INVERTER ORIGINAL REFER. EQUIVAL.
GH199A LJ97-00942A



Dimensiones / size : 286mm x 95mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	P.det.	on-off	Br.A	N.C


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTA260W3-L03 LTM260W3-L03

Marca / Brand	Model
SAMSUNG	

Observaciones / Remarks

HR I12L20005

INVERTER ORIGINAL REFER. EQUIVAL.
GH212A LJ97-01069A



Dimensiones / size : 272mm x 95mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	P.det.	on-off	Br.A	Pwm

CN8			
1	2	3	4
GND	on-off	Br.A	Pwm


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTA230W2-L01 LTM230W2-L0100R7

Marca / Brand	Model
SAMSUNG	

Observaciones / Remarks

HR I12L20006

INVERTER ORIGINAL REFER. EQUIVAL.
FIF2412-32A



Dimensiones / size : 272mm x 95mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.A	Pwm


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM240CT01 LTM240M1-L01/02- LTM240M2-L02
AUOPTRONICS	M240VW01 - M240J1-L02

Marca / Brand	Model
SAMSUNG	

Observaciones / Remarks

HR I12L20007

INVERTER ORIGINAL REFER. EQUIVAL.
VIT71007.50
19.26006.063



Dimensiones / size : 232mm x 110mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.A	on-off	Pwm	GND

CN2	
1	2
GND	GND

CN3	
1	2
Sinc.	GND


LCD panel manuf.	LCD Panel cod.

Marca / Brand	Model

Observaciones / Remarks

HR I14L20001

INVERTER ORIGINAL REFER. EQUIVAL.
VIT79005.81 19.26006.288



Dimensiones / size : 300mm x 100mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.A	on-off	Pwm	S.Br.

CN9	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
QDI	V26D3

Marca / Brand	Model

Observaciones / Remarks

HR I14L30001

INVERTER ORIGINAL REFER. EQUIVAL.
VIT79002.52 19.26006.286



Dimensiones / size : 320mm x 120mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.	GND

CN3	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
QDI	V32C5 V32C1-CD

Marca / Brand	Model

Observaciones / Remarks

HR I14L30002

INVERTER ORIGINAL REFER. EQUIVAL.
VIT79002.62 19.26006.137



Dimensiones / size : 320mm x 120mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.	GND

CN3	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
QDI	V32C5 V32C1-CD

Marca / Brand	Model

Observaciones / Remarks

HR I16L20001

INVERTER ORIGINAL REFER. EQUIVAL.
GH178A LJ97-01069A



Dimensiones / size : 360mm x 100mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.	St.L

CN2	
1	2
Br/Ctr	GND


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM270M1-L01

Marca / Brand	Model
SAMSUNG	

Observaciones / Remarks

HR I16L20002

INVERTER ORIGINAL REFER. EQUIVAL.
VIT71008.90
19.26006.111



Dimensiones / size : 300mm x 110mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.A	on-off	Pwm	GND

CN2	
1	2
Sinc.	GND


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	T260XW02

Marca / Brand	Model

Observaciones / Remarks

HR I16L20003

INVERTER ORIGINAL REFER. EQUIVAL.
VIT71008.91 19.26006.167



Dimensiones / size : 300mm x 110mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.A	on-off	Pwm	GND

CN2	
1	2
Sinc.	GND


LCD panel manuf.	LCD Panel cod.
SAMSUNG	T260XW02

Marca / Brand	Model
SAMSUNG	LN-S 2641D

Observaciones / Remarks

HR I16L20004

INVERTER ORIGINAL REFER. EQUIVAL.
VIT71008.92
19.26006.187



Dimensiones / size : 300mm x 110mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.A	on-off	Pwm	GND

CN2	
1	2
Sinc.	GND


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	T260XW02

Marca / Brand	Model

Observaciones / Remarks

HR I16L30001

INVERTER ORIGINAL REFER. EQUIVAL.
GH169A GH169C LJ97-01265A



Dimensiones / size : 360mm x 110mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.	St.L


LCD panel manuf.	LCD Panel cod.
SAMSUNG	LTM300M1-P01

Marca / Brand	Model
SAMSUNG	

Observaciones / Remarks

HR I16L30004

INVERTER ORIGINAL REFER. EQUIVAL.
VIT79001.52 19.26006.301



Dimensiones / size : 320mm x 120mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	on-off	Br.	GND

CN3	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
QDI	V32C1 V32D2

Marca / Brand	Model

Observaciones / Remarks

HR I16L30005

INVERTER ORIGINAL REFER. EQUIVAL.
VIT68001.80
632133718
4H.V1448.451/C1



Dimensiones / size : 370mm x 120mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.an.	on-off	Br.pw	Sel.

CN10	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
CHUNGHWA	CLAA320WF01T CLAA320WB02S

Marca / Brand	Model
SAMSUNG	LE32S62B

Observaciones / Remarks

HR I16L30006

INVERTER ORIGINAL REFER. EQUIVAL.
VIT68004.70
704100395
4H.V1838.491/B1



Dimensiones / size : 430mm x 105mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.an.	on-off	Br.pw	Sel.

CN10	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
CHUNGHWA	CLAA370WF01 CLAA370WA03S

Marca / Brand	Model
SAMSUNG	LE37S62B

Observaciones / Remarks

HR I18L30001

INVERTER ORIGINAL REFER. EQUIVAL.
VIT79006.60 19.26006.294



Dimensiones / size : 446mm x 95mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.an.	on-off	Br.pw	Sel.

CN11	
1	2
GND	Sinc.


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	V370A1

Marca / Brand	Model

Observaciones / Remarks

HR I20L30001

INVERTER ORIGINAL REFER. EQUIVAL.
VIT71010.53
19.26006.146



Dimensiones / size : 446mm x 105mm

Conecor Control / Control Connector CN1									
1	2	3	4	5	6	7	8	9	10
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND

Conector Control / Control Connector CN2													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Br.an.	on-off	Br.pw	Sel.

CN14	
1	2
GND	GND


LCD panel manuf.	LCD Panel cod.
AUOPTRONICS	T370XW01

Marca / Brand	Model

Observaciones / Remarks

HR I20L30002

INVERTER ORIGINAL REFER. EQUIVAL.
VIT70006.60
27-D005816
1370H1-24A-V00-L1E0



Dimensiones / size : 420mm x 120mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Sel.	E.pw.	I.pw.	on-off

Conector Control / Connector Control CN2											
1	2	3	4	5	6	7	8	9	10	11	12
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	N.C.

CN13	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
CHIMEI	T370H1-24A

Marca / Brand	Model

Observaciones / Remarks

HR I20L30003

INVERTER ORIGINAL REFER. EQUIVAL.
VIT70006.80
27-D015041
I370H2-24A-V01 / I370H1-20B-L001A



Dimensiones / size : 430mm x 125mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Sel.	E.pw.	I.pw.	on-off

Conector Control / Connector Control CN2											
1	2	3	4	5	6	7	8	9	10	11	12
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	N.C.

CN13	
1	2
L.ccfl	L.ccfl


LCD panel manuf.	LCD Panel cod.
CHIMEI	V370H1-L0A

Marca / Brand	Model

Observaciones / Remarks

HR I20L40001

INVERTER ORIGINAL REFER. EQUIVAL.
VIT70023.50/51
27-D005861
I420H1-L24-V01-L2D0



Dimensiones / size : 480mm x 100mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Sel.	E.pw.	I.pw.	on-off

Conector Control / Connector Control CN2											
1	2	3	4	5	6	7	8	9	10	11	12
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	N.C.


LCD panel manuf.	LCD Panel cod.
CHIMEI	V420H1-L24

Marca / Brand	Model

Observaciones / Remarks

HR I20L40002

INVERTER ORIGINAL REFER. EQUIVAL.
VIT70023.60/61
27-D013345
I420H1-20C-L001A



Dimensiones / size : 480mm x 100mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Sel.	E.pw.	I.pw.	on-off

Conector Control / Connector Control CN2											
1	2	3	4	5	6	7	8	9	10	11	12
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	N.C.


LCD panel manuf.	LCD Panel cod.
CHIMEI	V420H1-L05

Marca / Brand	Model

Observaciones / Remarks

HR I20L40003

INVERTER ORIGINAL REFER. EQUIVAL.
VIT70023.70/71 I420H1-20A-L201C 27-D010638



Dimensiones / size : 480mm x 100mm

Conector Control / Control Connector CN1													
1	2	3	4	5	6	7	8	9	10	11	12	13	14
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	Sel.	E.pw.	I.pw.	on-off

Conector Control / Connector Control CN2											
1	2	3	4	5	6	7	8	9	10	11	12
24V	24V	24V	24V	24V	GND	GND	GND	GND	GND	N.C.	N.C.


LCD panel manuf.	LCD Panel cod.
CHIMEI	V420H1

Marca / Brand	Model

Observaciones / Remarks

HR IP2L100001

INVERTER ORIGINAL REFER. EQUIVAL.
AI-0021A
3138 188 79062



Dimensiones / size : 150mm x 125mm

Conector Control / Control Connector CN001									
1	2	3	4	5	6	7	8	9	10
GND	Br.	on-off	P. Id.	N.C	GND	12V	GND	3,3V	3,3V

JACK 001		
1	2	3
12V	GND	GND


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	
CHUNGHWA	
HANNSTAR	

Marca / Brand	Model

Observaciones / Remarks

HR IP2L100002

INVERTER ORIGINAL REFER. EQUIVAL.
AI-0067A 3138 198 74361



Dimensiones / size : 135mm x 115mm

Conector Control / Control Connector CON101										
1	2	3	4	5	6	7	8	9	10	11
GND	Br.	on-off	P. Id.	GND	12V	12V	GND	3,3V	3,3V	GND


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	
CHUNGHWA	
HANNSTAR	

Marca / Brand	Model

Observaciones / Remarks

HR IP2L100003

INVERTER ORIGINAL REFER. EQUIVAL.
AI-0097
3138 198 76371



Dimensiones / size : 135mm x 115mm

Conector Control / Control Connector CON101										
1	2	3	4	5	6	7	8	9	10	11
GND	Br.	on-off	P. Id.	GND	12V	12V	GND	3,3V	3,3V	GND


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	
CHUNGHWA	
HANNSTAR	

Marca / Brand	Model

Observaciones / Remarks

HR IP4L100001

INVERTER ORIGINAL REFER. EQUIVAL.
AIP-0093 3138 198 75863



Dimensiones / size : 150mm x 135mm

Conector Control / Control Connector CON301										
1	2	3	4	5	6	7	8	9	10	11
GND	Br.pw	BL	on-off	GND	12V	12V	GND	5V	5V	GND


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
PHILIPS	

Observaciones / Remarks

HR IP4L100002

INVERTER ORIGINAL REFER. EQUIVAL.
AIP-0095 FE572A306A0001



Dimensiones / size : 173mm x 125mm

Conector Control / Control Connector CN303										
1	2	3	4	5	6	7	8	9	10	11
Br.A	Br.pw	on-off	N.C.	GND	5V	5V	GND	GND	12V	12V


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
LG	

Observaciones / Remarks

HR IP4L100006

INVERTER ORIGINAL REFER. EQUIVAL.
AI-0031F FE5319C249G0885



Dimensiones / size : 198mm x 123mm

Conector Control / Control Connector CON002										
1	2	3	4	5	6	7	8	9	10	11
12V	12V	GND	GND	5V	5V	GND	5V	on-off	Br. A	N.C.


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
LG VESTEL	

Observaciones / Remarks

HR IP4L100007

INVERTER ORIGINAL REFER. EQUIVAL.
AIP-0105N FE6427A324N0406



Dimensiones / size : 188mm x 123mm

Conector Control / Control Connector CON002										
1	2	3	4	5	6	7	8	9	10	11
12V	12V	GND	GND	5V	5V	GND	5V	on-off	Br.pw	Br.A


LCD panel manuf.	LCD Panel cod.
LG-PHILPS	

Marca / Brand	Model
LG VESTEL	

Observaciones / Remarks

HR IP6L200001

INVERTER ORIGINAL REFER. EQUIVAL.
AIV-0001A FE7025O280K1075



Dimensiones / size : 156mm x 145mm

Conector Control / Control Connector CON202										
1	2	3	4	5	6	7	8	9	10	11
15V	15V	GND	GND	5V	5V	GND	N.C.	on-off	Br.A	ILC


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
PHILIPS	

Observaciones / Remarks

HR IP6L200002

INVERTER ORIGINAL REFER. EQUIVAL.
AIVP-0010 FE5N02C319A



Dimensiones / size : 156mm x 145mm

Conector Control / Control Connector CW201										
1	2	3	4	5	6	7	8	9	10	11
15V	15V	GND	GND	5V	5V	GND	N.C.	on-off	Br.pw	Br.A


LCD panel manuf.	LCD Panel cod.
LG-PHILPS	

Marca / Brand	Model
LG	

Observaciones / Remarks

HR IP6L200003

INVERTER ORIGINAL REFER. EQUIVAL.
AIVP-0026 AIVP-0026C 30057403 30051308



Dimensiones / size : 230mm x 105mm

Conector Control / Control Connector CN201									
1	2	3	4	5	6	7	8	9	10
5V	5V	GND	GND	GND	GND	12V	12V	on-off	Br. A


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS SAMSUNG	

Marca / Brand	Model
SANYO VESTEL	CE20LD51C CH.17MB24-3

Observaciones / Remarks

HR IP6L200004

INVERTER ORIGINAL REFER. EQUIVAL.
AIVP-0006C FE6406A280G0179



Dimensiones / size : 156mm x 145mm

Conector Control / Control Connector CON202										
1	2	3	4	5	6	7	8	9	10	11
15V	15V	GND	GND	5V	5V	GND	N.C.	on-off	Br.pw	Br.A


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
LG	

Observaciones / Remarks

HR IP6L200005

INVERTER ORIGINAL REFER. EQUIVAL.
AIV-0009A FE7026N280Q0161



Dimensiones / size : 156mm x 155mm

Conector Control / Control Connector CON202										
1	2	3	4	5	6	7	8	9	10	11
15V	15V	GND	GND	5V	5V	GND	N.C.	on-off	Br.A	ILC


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
PHILIPS	

Observaciones / Remarks

HR IP6L200006

INVERTER ORIGINAL REFER. EQUIVAL.
AIVP-0032A E7ND0326364020033



Dimensiones / size : 156mm x 145mm

Conector Control / Control Connector CON202										
1	2	3	4	5	6	7	8	9	10	11
15V	15V	GND	GND	5V	5V	GND	N.C.	on-off	Br.A	ILC


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
VESTEL	

Observaciones / Remarks

HR IP6L200009

INVERTER ORIGINAL REFER. EQUIVAL.
AIP-0110A FE7425A325A0013



Dimensiones / size : 2000mm x 155mm

Conector Control / Control Connector CW201										
1	2	3	4	5	6	7	8	9	10	11
15V	15V	GND	GND	5V	5V	GND	N.C.	on-off	Br.pw	Br.A


LCD panel manuf.	LCD Panel cod.
LG-PHILIPS	

Marca / Brand	Model
LG	

Observaciones / Remarks

HR IP16L30001

INVERTER ORIGINAL REFER. EQUIVAL.
AIVP0035A 30053669



Dimensiones / size : 382mm x 170mm

Conector Control / Control Connector CN4												
1	2	3	4	5	6	7	8	9	10	11	12	13
5V	5V	5V	3,3V	3,3V	3,3V	GND	GND	GND	GND	3,3V	3,3V	5V

Conector Control / Control Connector CN3							
1	2	3	4	5	6	7	8
on-off	Br.A	Br pw	33V	12V	12V	GND	GND

CN2			
1	2	3	4
GND	GND	24V	24V

LCD panel manuf.	LCD Panel cod.
AUOPTRONICS CHUNGHWA	

Marca / Brand	Model


Observaciones / Remarks

If you need more information on Computer and Electronic Repair, please visit these websites to improve yourself.

http://www.fastrepairguide.com
http://www.protech2u.com
http://www.plasma-television-repair.com
http://www.lcd-television-repair.com

Happy Repairing!!


Highly Recommended Repair Ebook:



If you're a LCD Monitor repairer, then this is the best guide for you. Why? Because, the author revealed all his LCD Monitor Repairing secrets for you. I think, with just few Repair tips you learned from this guide you will get back your investment!
Click Here to read more.



This eBook will show you how to test the electronic component correctly and accurately. Some of you may say that I don't need this eBook because it is too simple! Do you know that, in fact there is lots of testing electronic components secrets I have learned from this guide? Do you know how to test a'TRIAC' correctly and accurately? If you answer no then I guess you have to get this EBook. Click Here to read more.



Are you tired of searching the service manuals to look for the value of a burnt resistor? If the answer is YES, then this eBook is a 'must have' guide for you. You can save a lot of time and be able to repair customer's Electronic equipment with burnt resistors in it.
Click here to read more.