



11 Disassembly and Reassembly





This section of the service manual describes the disassembly and reassembly procedures for the TFT-LCD TV.



⚠ WARNING : This monitor contains electrostatically sensitive devices. Use caution when handling these components.





11-1 Disassembly


- ⚠ Cautions :**
- 1. Disconnect the monitor from the power source before disassembly.
 - 2. Follow these directions carefully; never use metal instruments to pry apart the cabinet.

Description	Picture Description
1. Place monitor face down on cushioned table. Remove screws from the rear cover. Remove screws from the stand.	
	

Description	Picture Description
2. Lift up the rear cover and remove the stand.	
	
3. Remove Screws from the stand BRKT and lift up the stand BRKT.	
	

Description	Picture Description
<p>4. Disconnect cable from the boards.</p>	 <p>The image shows the internal components of a device. A green main board is on the right, and a yellow power board is on the left. Red circles highlight specific connection points: one on the top right of the green board, one on the bottom left of the green board, one on the bottom right of the green board, and one on the bottom left of the yellow board.</p>
<p>5. Remove screws from the boards and lift up the boards.</p>	 <p>The top image shows the green main board with four red circles highlighting screws to be removed: two on the top edge and two on the bottom edge. The bottom image shows the yellow power board with three red circles highlighting screws to be removed: one on the top edge, one on the bottom edge, and one on the right side.</p>

Description	Description Picture
<p>6. Remove screws and Lift up the Lcd panel.</p>	
	
<p>7. Remove 5 screws from the BRKT. Lift up the BRKT.</p>	
	

Description	Description Picture
	

11-2 Reassembly

Reassembly procedures are in the reverse order of disassembly procedures.

Memo